

New light engine for Panelview 550





IMPORTANT:

WARRANTY

Before using any MONITECH product please carefully review this Manual as well as any additional documentation provided with your shipment.

Attempting any of the following will void product warranty:

- unauthorized repairs or parts replacement
- inappropriate use or placement: exposing product to liquids, harmful gases, electrical shock, physical shock, temperatures beyond the range of -4°F to 140°F (-20°C to 60°C)
- use of electrical voltage other than 12V 4.16A (power supply and AC cable provided)
- Removal or modification of serial, product, or warranty labels.

	WARNING ELECTRICAL HAZARD DO NOT OPEN	
TO AVOID ELECTRICAL SHOCK DO NOT OPEN PRODUCT CASING. UNAUTHORIZED REPAIRS OR PARTS REPLACEMENT ARE PROHIBITED AND WILL VOID PRODUCT WARRANTY. PLEASE RETURN TO MONITECH FOR REPAIRS.		

Step #1) Turn off the machine that your AB Panelview 550 terminal is on. Turn off main power.



Step #2) Unplug your AB Panelview 550 terminal main power and controller power.



Unplug
main
power.




Unplug
controller
power.

Step #3) Unfasten all the nuts around the AB Panelview 550 terminal, to do the installation on your bench, but if not skip to Step #4. Keep all the nuts removed for re-installation.





Unscrew
these
fasteners.

Step #4) Now you have your AB Panelview 550 terminal on your bench or on your machine. Open the backlight cover of the terminal. Be careful it could be hot!!!.



Step #5) Now remove the Fiber Optics from mounting, and remove old backlight from mounting, Unscrew mounting and keep screws for install of your new backlight.



INSTALLATION:

Step 6) Install new MB550E backlight engine on to your backcover.




Step #7) Attach fibre optic and tighten set screw.



Step #8) Connect the backlight cable to the controller backlight connector directly. Test it using the main power, plug it into a wall plug. If the new backlight turns ON, Then put backlight cover back on. If not turned on, please follow Step #9.



Step #9) If the backlight doesn't come on, then, use the reverse polarity connector provided in the package. Unplug the backlight from the controller and connect the reverse polarity connector onto the backlight cable connector and then connect the backlight to the controller backlight connector and test it.



**REVERSE POLARITY
CONNECTOR**

Step #10) Use the nuts to fasten your AB Panelview 550 terminal back on to your machine. Plug in controller power and plug in main power. Then turn machine power on.



YOU ARE ALL SET
MONITECH THANKS YOU FOR YOUR BUSINESS.

Enjoy your rejuvenated Monitor.
Call us to order more replacement parts.

Keep your Panelview 550 up and running!



LED backlight MB550E



Fiber optic MB550FOS



Fiber optic MB55FOL



Touchscreen MF550T



Keypad MF550K



Keypad-touchscreen
MF550B

For Technical Support, Call
1-877-493-6105
Support@Monitech.com

For Technical Support, Call Us.

MONITECH

20 Howard Place
Kitchener, Ontario N2X 4Z4
CANADA 519.725.2222
www.monitech.com